

(19) World Intellectual Property Organization
International Bureau



(43) International Publication Date
2 August 2001 (02.08.2001)

PCT

(10) International Publication Number
WO 01/56263 A1

(51) International Patent Classification⁷: **H04M 9/08**,
H04B 3/23

(21) International Application Number: PCT/US01/02749

(22) International Filing Date: 26 January 2001 (26.01.2001)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
09/491,933 27 January 2000 (27.01.2000) US

(71) Applicant: **QUALCOMM INCORPORATED** [US/US];
5775 Morehouse Drive, San Diego, CA 92121-1714 (US).

(72) Inventor: **GUPTA, Samir, K.**; 13593 Tiverton Road, San
Diego, CA 92130 (US).

(74) Agents: **WADSWORTH, Philip, R.** et al.; Qualcomm In-
corporated, 5775 Morehouse Drive, San Diego, CA 92121-
1714 (US).

(81) Designated States (*national*): AE, AG, AL, AM, AT, AU,
AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CR, CU, CZ,
DE, DK, DM, DZ, EE, ES, FI, GB, GD, GE, GH, GM, HR,
HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR,
LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ,
NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM,
TR, TT, TZ, UA, UG, UZ, VN, YU, ZA, ZW.


(84) Designated States (*regional*): ARIPO patent (GH, GM,
KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZW), Eurasian
patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European
patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE,
IT, LU, MC, NL, PT, SE, TR), OAPI patent (BF, BJ, CF,
CG, CI, CM, GA, GN, GW, ML, MR, NE, SN, TD, TG).

Published:

- with international search report
- before the expiration of the time limit for amending the
claims and to be republished in the event of receipt of
amendments

For two-letter codes and other abbreviations, refer to the "Guid-
ance Notes on Codes and Abbreviations" appearing at the begin-
ning of each regular issue of the PCT Gazette.

(54) Title: **IMPROVED SYSTEM AND METHOD FOR IMPLEMENTATION OF AN ECHO CANCELLER**



(57) **Abstract:** A system and method for cancelling an echo signal. An input waveform is provided to an acoustic processor, and a determination is made whether the input waveform includes information representative of an echo signal. If the input waveform includes information representative of an echo signal, an output waveform is formed by attenuating a residual waveform with the acoustic processor. The residual waveform is attenuated by an attenuation factor that gradually changes from an initial attenuation value to a final attenuation value during the attenuation step. A system and method for adjusting an acoustic signal from a muted state to an unmuted state by varying an attenuation factor applied to an acoustic signal by an acoustic processor. The acoustic signal is provided to an acoustic processor. An output waveform is formed from the acoustic processor by adjusting the attenuation factor from a muted state to a first attenuation value associated with the non-muted state. After the attenuation factor is adjusted to the first attenuation value, the output waveform is formed by gradually changing the attenuation factor from the first attenuation value to a second attenuation value. The input waveform is attenuated by a smaller amount when the second attenuation value is applied to the acoustic signal than when the first attenuation value is applied to the acoustic signal.

IMPROVED SYSTEM AND METHOD FOR IMPLEMENTATION OF AN ECHO CANCELLER

Background of the Invention

I. Field of the Invention

5 The present invention relates generally to echo cancellers. More particularly, the present invention relates to a novel and improved system and method for reducing the chopiness heard in full-duplex systems that use echo cancellers. The teachings of the present invention apply to acoustic echo cancellers, as well as to echo cancellers in networks and other non-acoustic
10 systems.

II. Description of the Related Art

 Acoustic echo-cancellers (AEC) are used in teleconferencing and hands-free telephony applications to eliminate acoustic feedback between a loudspeaker and a microphone. In a cellular telephone system where the driver
15 uses a hands-free telephone, acoustic echo cancellers are used in the mobile station to provide full-duplex communications. A block diagram of a traditional acoustic echo canceller is illustrated in FIG. 1.

 For reference purposes, the driver is the near-end talker with input speech signal $v(n)$ and the person at the other end of the connection is the far-
20 end talker with input digital speech signal $x(n)$. The speech of the far-end talker is broadcast out of loudspeaker 2 in the mobile telephone. If this speech is picked up by microphone 10, the far-end talker hears an annoying echo of his or her own voice. The output of microphone 10, $r(n)$, is a digital signal. Typically the functions performed by microphone 10 may be accomplished by a

microphone, which would convert the audio signal to an analog electrical signal and an analog to digital (A/D) converter. The AEC identifies the impulse response between speaker 2 and microphone 10, generates a replica of the echo using adaptive filter 14, and subtracts it in summer 12 from the microphone
5 output, $r(n)$, to cancel the far-end talker echo $y(n)$. Since the adaptive filter cannot generally remove all of the echo, some form of echo suppression provided by residual echo suppression element 18 (e.g., a non-linear post processor) is typically employed to remove any residual echo.

In FIG. 1, the far end talker echo signal $y(n)$ is illustrated as the output of
10 an acoustic echo path element 4, which is an artifact of the proximity of the loudspeaker 2 and microphone 10. To the far end talker echo signal $y(n)$ is added noise signal $w(n)$ and near-end speech signal $v(n)$, illustrated by summing elements 6 and 8 respectively. It should be noted that summing elements 6 and 8 and acoustic echo path 4 are artifacts of the mobile
15 environment and are presented for illustrative purposes.

Adaptive filter 14 uses the far-end speech $x(n)$ as a reference signal. If adaptive filter 14 is allowed to adapt in the presence of $v(n)$, the near-end speech will be added to the error signal $e(n)$, which drives the filter tap coefficient adaptation, corrupting the estimate of acoustic echo path 4. It is
20 therefore necessary to disable coefficient adaptation when both talkers are speaking, a condition referred to as doubletalk. During doubletalk, residual echo suppression element 18 must also be disabled to prevent corruption of the near-end speech. A doubletalk detector (not shown) typically detects the

presence of doubletalk and provides control signals to disable adaptive filter 14 and residual echo suppression element 18 when doubletalk is present.

As shown in FIG. 2, in prior art echo cancellation systems, residual echo suppression element 18 functions to cancel any residual echo by muting (i.e., gating-off) its output whenever an echo is detected by the adaptive filter 14. This aspect of element 18 is shown in portion "A" of FIG. 2. The upper half of portion "A" of FIG.2 illustrates the detection of an echo condition resulting from acoustic feedback between loudspeaker 2 and a microphone 10 when the word "HELLO" is spoken by a far-end talker. The lower half of portion "A" of FIG. 2 shows that, as soon as the echo is detected at t_1 , the output of element 18 is muted-off entirely. Thereafter, as soon as the echo ceases to be present at t_2 , the output of element 18 is unmuted.

In addition, in instances where the output of residual echo suppression element 18 is muted because adaptive filter 14 has detected an echo and the double-talk detector simultaneously detects double-talk, residual echo suppression element 18 will unmute its output during the double-talk period. This aspect of element 18 is shown in portion "B" of FIG. 2. The upper half of portion "B" of FIG.2 illustrates the detection of a double-talk condition at t_4 at a time when the output of element 18 is being muted as a result of the detection of an echo condition between t_3 and t_4 . The double-talk condition results from simultaneous speech by the far-end and near-end talkers (i.e, the near-end talker is saying "HI" during the time that the far-end talker is saying "HELLO"). The lower half of portion "B" of FIG. 2 shows that, as soon as the double-talk is detected at t_4 , the output of element 18 is unmuted. Thereafter, as

soon as the double-talk condition ceases to be present at t_5 , the output of element 18 is muted again. The output of element 18 remains fully muted until the echo resulting from the word "HELLO" spoken by the far end talker ceases at t_6 . As soon as the echo ceases to be present at t_6 , the output of element 18 is unmuted.

Portion "C" of FIG. 2 similarly illustrates an example where the output of element 18 remains unmuted when a double-talk condition is detected between t_7 and t_8 . Thereafter, as soon as the double-talk condition ceases to be present at t_8 , the output of element 18 is muted again because of an ongoing echo condition. The output of element 18 remains fully muted until this echo condition ceases at t_9 , thereby causing muting of the word "UP" from the near-end talker between t_8 and t_9 . As soon as the echo ceases to be present at t_9 , the output of element 18 is unmuted.

Referring still to the prior art system of Figure 1, when the echo component $y(n)$ dominates the near-end speech signal $v(n)$ during particular periods, the near-end speech will be muted out by element 18. This situation can result in an undesirable chopiness in the audible signal heard by the user. One purpose of the present invention is smooth this chopiness, which can be unpleasant and annoying to the user.

In addition to be annoying to the user, this chopiness often results in the presentation of an unsmooth energy curve to the vocoder used for encoding the near-end speech signal. In applications where variable rate vocoders are used, the chopiness in the energy curve can cause the vocoder to transmit at the full data rate more often than is necessary, thereby wasting limited system capacity.

Thus, it is a further object of the present invention to present a smoother energy curve to the vocoder, thereby improving its performance.

These problems and deficiencies are recognized and solved by the present invention in the manner described below.

5

Summary of the Invention

One aspect of the present invention is directed to a system and method for canceling an echo signal. This aspect of the invention may be used, for example, for removing an abrupt transition in the audible signal that would otherwise occur when the near-end speech signal is dominated by an echo and
10 the output of the non-linear post-processor is being changed from a non-muted to a muted state. According to this aspect of the invention, an input waveform is provided to an acoustic processor, and a determination is made whether the input waveform includes information representative of an echo signal. If the input waveform includes information representative of an echo signal, an
15 output waveform is formed by attenuating a residual waveform with the acoustic processor. The residual waveform is attenuated by an attenuation factor that gradually changes from an initial attenuation value to a final attenuation value during the attenuation step. This aspect of the invention may also be used, for example, for removing the chopiness in the audible signal that
20 would otherwise occur when the near-end speech is dominated by an echo and the output of the non-linear post-processor is being changed for a non-muted to a muted state.

In accordance with a further aspect, the present invention is directed to a system and method for adjusting an acoustic signal from a muted state to an unmuted state by varying an attenuation factor applied to an acoustic signal by an acoustic processor. This aspect of the invention may be used, for example, for removing the chopiness in the audible signal that would otherwise occur when the end of an echo condition is detected and the output of the non-linear post-processor is being changed from a muted to a non-muted state. According to this aspect of the invention, an acoustic signal is provided to an acoustic processor, and an output waveform is formed from the acoustic processor by adjusting the attenuation factor from the muted state to a first attenuation value associated with the non-muted state. After the attenuation factor is adjusted to the first attenuation value, the output waveform is formed by gradually changing the attenuation factor from the first attenuation value to a second attenuation value. The input waveform is attenuated by a smaller amount when the second attenuation value is applied to the acoustic signal than when the first attenuation value is applied to the acoustic signal. This aspect of the invention may also be used, for example, for removing the chopiness in the audible signal that might otherwise result when a mobile phone is operating in AMPS mode and bursty noise is present.

20

Brief Description of the Drawings

The features, objects and advantages of the present invention will become more apparent from the detailed description set forth below when taken in conjunction with the drawings in which like reference characters

identify correspondingly throughout and wherein:

Figure 1 is a block diagram of a prior art acoustic echo canceller.

Figure 2 is a timing diagram showing the operation of the prior art residual echo suppression element shown in Figure 1.

5 Figure 3 is a block diagram of a novel non-linear post processor that functions in accordance with a preferred embodiment of the present invention.

Figure 4 is a flow diagram showing the method of operation of the non-linear post processor shown in Figure 3.

10 Figure 5 is a timing diagram showing the operation of the non-linear post-processor shown in Figure 3 in instances where echo and double-talk conditions are present.

Figure 6 is a timing diagram showing the operation of the non-linear post-processor of Figure 3 when bursty noise is present at the far-end talker.

15 Detailed Description of the Preferred Embodiments

Referring now to Figure 3, there is shown a block diagram of an acoustic processor 300 that functions in accordance with a preferred embodiment of the present invention. Acoustic processor 300 is a non-linear post processor that accepts as its input, for example, the error signal $e(n)$ described above in connection with Figure 1. Acoustic processor 300 includes a switch 310 for varying the state of the processor between an off state and an up/down state. When acoustic processor 300 is operating in its off state, the input signal $e(n)$ is applied to a muting means 320 which functions to

20

completely gate-off the input signal, thereby producing an output signal at the output of processor 300 that is entirely muted off. When acoustic processor 300 is operating in its up/down state, the input signal $e(n)$ is applied to a variable attenuator 330 which produces an output signal by partially attenuating the input signal. The attenuation factor (k) that is applied to the input signal by the variable attenuator 330 is calculated and adjusted using method 400 shown in Figure 4. As explained more fully below, the variable attenuator 330 has three states, namely UP, DOWN and OFF. These states are alternatively used depending on whether the variable attenuator is ramping-up the attenuation factor (k) being applied to the input signal (k), ramping-down the attenuation factor (k) that is being applying to the input signal $e(n)$, or off.

Referring now to Figure 4, there is shown a flow diagram illustrating a method 400 of operation of the acoustic processor shown in Figure 3. Method 400 is used to control switch 310 (thereby switching the processor between its off and up/down states) and to vary the attenuation factor (k) applied to the input signal by the variable attenuator 330. Method 400 may be implemented in software using controller 340 in acoustic processor 300. Method 400 is particularly well-suited for controlling an acoustic processor used for processing signals sent between a base station and a mobile telephone using CDMA modulation. The use of CDMA techniques in a multiple access communication system is well known and disclosed, for example, in U.S. Pat. No. 4,901,307, entitled "SPREAD SPECTRUM MULTIPLE ACCESS COMMUNICATION SYSTEM USING SATELLITE OR TERRESTRIAL

REPEATERS," assigned to the assignee of the present invention and incorporated by reference herein.

Referring still to Figure 4, in step 402, the system tests whether processor 300 is about to begin attenuating the input signal $e(n)$. Step 402 will determine that attenuation of the input signal $e(n)$ is about to begin, for example, when an echo condition is first detected by adaptive filter 14, when bursty noise is present at the far-end talker or when an echo condition remains present following the end of a double-talk period. If a determination is made in step 402 that the attenuating of the input signal is about to begin, then processing proceeds to step 404 where the state of processor 300 is set to up/down (i.e., switch 310 directs the input signal to variable attenuator 330), the state of variable attenuator is set to UP, and the current value of the attenuation factor (k) applied to the input signal by attenuator 330 is set to 0 db. Next, in step 406, the current value of the attenuation factor (k) is compared to a threshold k_{up} which is calculated in accordance with equation (1) below:

$$K_{up} = \alpha ((M * 2^{32} * bnS * G_{pred}) / (12 * E))^{0.5} \quad (1)$$

where E represents an energy estimate of the input waveform $e(n)$ over M samples, bnS is a background noise scale value associated with the uniformly distributed random noise generator used for generating $w(n)$, and G_{pred} is the prediction gain of a LPC shaping filter associated with the CDMA modulation used for transmission and reception of the speech signal $x(n)$ between a base station and a mobile station. The constant α is preferably set to 1.0. In alternate embodiments where it is desirable to cause the attenuation of $e(n)$ to ramp-up

more quickly, α will preferably be set to a value greater than 1.0. The values b_nS and G_{pred} are preferably calculated as set forth in U.S. Patent No. 5,646,691, entitled "Noise Replacement Ssystem in an Echo Canceller," incorporated herein by reference.

5 If in step 406 it is determined that the current value of the attenuation factor (k) is not less than threshold k_{up} , then processing proceeds back to step 402. In cases where a determination was made in the previous iteration of step 402 that the attenuating of the input signal $e(n)$ was about to begin, the current state of variable attenuator 330 will be set to UP, the testing in step 402 will
10 return a NO value and the testing in step 408 (which tests to determine if attenuation of the input signal has just ended) will similarly return a NO value. In such cases, processing thereafter proceeds to step 410 which tests to determine if the current state of the variable attenuator is UP. If the current state of the variable attenuator is UP, then in step 412 the current value of the
15 attenuation factor (k) applied to the input signal is ramped-up. In a preferred embodiment, the attenuation factor is ramped-up an amount equal to -1.5 db / 5 msec interval; however, it will be understood by those skilled in the art that the ramp-up amount applied to k in each iteration of step 412 is a matter of design choice and may be greater or less than -1.5 db per step. Next, in step
20 406, the current value of the attenuation factor (k) is compared to the threshold k_{up} . If in step 406 it is determined that the current value of the attenuation factor (k) is not less than threshold k_{up} then the processing loop described above continues to repeat until, as a result of repeated ramping of the value of k in

step 412, the current value of the attenuation factor (k) is determined to be less than the threshold k_{up} in step 406.

When the current value of the attenuation factor (k) is determined to be less than the max of the threshold k_{up} or gamma (e.g., gamma = 30dB) in step 406, then in steps 414 and 416, the state of processor 300 is changed from its up/down to its off state (i.e., switch 310 redirects the input signal from variable attenuator 330 to muting means 320), the current value of the attenuation factor (k) is reset to 0, and the state of variable attenuator 330 is set to OFF.

Thus, in cases where the attenuating of the input signal $e(n)$ is initiated because, for example, an echo condition is first detected by adaptive filter 14, bursty noise is present at the far-end talker or an echo condition remains present following the end of a double-talk period, the attenuation is ramped-up gradually (in a step-wise manner at -1.5 db / 5 msec interval) until the current value of the attenuation factor reaches k_{up} , at which point the input signal is entirely muted. An example of this aspect of the invention is illustrated in Figure 5 which shows the gradual ramping-up of the attenuation factor (k) starting at t_1 when an echo condition first begins. The gradual ramping-up of the attenuation factor (k) continues from t_1 until t_2 , when the value of the attenuation factor (k) reaches k_{up} . Immediately following t_2 , the variable attenuator 330 is turned off and the input signal is entirely muted (i.e., gated-off). By gradually ramping-up the attenuation factor (k) prior to gating-off the input signal at t_2 , the present invention substantially reduces the "chopiness" in the audible signal that is typically heard by users of prior art echo cancellers.

The gradual ramping-up of the attenuation factor (k) when an echo condition first begins is also shown as occurring from t_5 to t_6 in Figure 5.

In Figure 5 there is also shown an example of the operation of the present invention in a case where an echo condition remains present following the end of a double-talk period. In particular, at t_{11} the double-talk condition resulting from simultaneous uttering of "HEY" (by the far-end talker) and the beginning of the phrase "WHAT'S UP" by the near-end talker, ceases to exist. However, at this same time, an echo condition remains as a result of, for example, acoustic coupling of speaker 2 and microphone 10. Gradual ramping-up of the attenuation factor (k) starts at t_{11} when the double-talk period ends and the echo condition remains present. The gradual ramping-up of the attenuation factor (k) continues from t_{11} until t_{12} , when the value of the attenuation factor (k) reaches k_{up} . Immediately following t_{12} , the variable attenuator 330 is turned off and the input signal is entirely muted (i.e., gated-off). Significantly by gradually ramping-up the attenuation prior to gating-off the input signal at t_{12} , the present invention permits the portion of the phrase "WHAT'S UP" (from the near-end talker) remaining after cessation of the double-talk period to be transmitted through processor 300, albeit in a partially attenuated form. This result stands in contrast to that achieved by prior art residual echo suppression element 18 (shown in Figure 2) which, in the identical situation, would entirely gate-off the input signal following cessation of the double-talk period (cessation of the double-talk period occurs at t_8 in Figure 2) thereby precluding any portion of the phrase "WHAT'S UP" (from the near-end talker) remaining after

cessation of the double-talk period to be transmitted through to the far-end talker. In addition, by gradually ramping-up the attenuation factor (k) prior to gating-off the input signal at t_{12} , the present invention substantially reduces the “chopiness” in the audible signal that is typically heard by users of prior art

5 echo cancellers.

Referring again to Figure 4, in step 408, the system tests whether processor 300 is about to cease muting the input signal $e(n)$. Step 408 will determine that the attenuation of the input signal $e(n)$ is about to cease, for example, when adaptive filter 14 determines that a previously detected echo

10 condition is no longer present, when previous bursty noise at the far-end talker ceases to be present or when a double-talk period begins during the existence of an echo condition. If a determination is made in step 408 that the attenuating of the input signal is about to cease, then processing proceeds to step 418 where the state of the variable attenuator is changed to DOWN. In step 420, the

15 system tests to determine if the previous state of the variable attenuator 330 was UP. If so, processing proceeds to step 422 where the state of processor 300 is set to up/down (i.e., switch 310 directs the input signal to variable attenuator 330), and the current value of the attenuation factor (k) applied to the input signal by attenuator 330 is set to k_{down} , where k_{down} is calculated in accordance with

20 equation (2) below:

$$k_{down} = B((M * 2^{32} * bnS * G_{pred}) / (12 * E))^{0.5} \quad (2)$$

where E represents an energy estimate of the input waveform over M samples, bnS is a background noise scale value for the uniformly distributed random

noise generator used for generating $w(n)$, and G_{pred} is the prediction gain of a LPC shaping filter associated with the CDMA modulation used for transmission and reception of the speech signal $x(n)$ between a base station and a mobile station. The constant B is preferably set to 1.0. In alternate
5 embodiments where it is desirable to cause the attenuation of $e(n)$ to ramp-down more quickly, B will preferably be set to a value greater than 1.0.

Next, processing proceeds back to step 402. In cases where a determination was made in the previous iteration of step 408 that the attenuating of the input signal $e(n)$ was about to cease, the current state of
10 variable attenuator 330 will be set to DOWN, the testing in step 402 will return a NO value and the testing in step 408 will similarly return a NO value. In such cases, processing thereafter proceeds to step 426 which tests to determine if the current state of the variable attenuator is DOWN. If the current state of the variable attenuator is DOWN, then in step 428 the current value of the
15 attenuation factor (k) applied to the input signal is ramped-down. In a preferred embodiment, the attenuation factor is ramped-down an amount equal to 1.5 dB / 5 msec interval; however, it will be understood by those skilled in the art that the ramp-down amount applied to k in each iteration of step 428 is a matter of design choice and may be greater or less than 1.5 db per step. Next, in
20 step 430, the current value of the attenuation factor (k) is compared to 0 db. If in step 430 it is determined that the current value of the attenuation factor (k) is less than 0 db, then the processing loop described above continues to repeat until, as a result of repeated ramping of the value of k in step 428, the current

value of the attenuation factor (k) is determined to be greater than or equal to 0 db in step 430. When the current value of the attenuation factor (k) is determined to be greater than or equal to 0 db in step 430, then in step 416 the state of variable attenuator 330 is set to OFF.

- 5 Thus, in cases where the attenuating of the input signal $e(n)$ is terminated because, for example, adaptive filter 14 determines that a previously detected echo condition is no longer present, bursty noise that was previously present at the far-end source ceases to be present or a double-talk period begins during the existence of an echo condition, the attenuation factor is initially set to k_{down} .
- 10 Thereafter, the attenuation factor is ramped-down gradually (in a step-wise manner at 1.0 dB / 5 msec interval) until the current value of the attenuation factor reaches 0 dB. An example of this aspect of the invention is illustrated in Figure 5 which shows the setting of the attenuation factor to k_{down} at t_3 when an echo condition first ceases and thereafter the gradual ramping-down of the
- 15 attenuation factor (k) until t_4 when the attenuation factor (k) reaches 0 db. By gradually ramping-down the attenuation factor until reaching 0 db at t_4 , the present invention substantially reduces the "chopiness" in the audible signal that is typically heard by users of prior art echo cancellers. Examples where, upon cessation of an echo condition, the attenuation factor (k) is initially set to
- 20 k_{down} and then gradually ramped-down until it reaches 0 db are also shown as occurring from t_9 to t_{10} and from t_{13} to t_{14} in Figure 5.

In Figure 5 there is also shown an example of the operation of the present invention in a case where a double-talk period begins during the

existence of an echo condition. In particular, at t_7 , a double-talk condition begins as a result of the phrase "HI" being spoken by the near-end talker while the phrase "HELLO" is being spoken by the far-end talker. However, immediately preceeding t_7 , an echo condition already existed as a result of the uttering of the beginning of the phrase "HELLO" by the far-end talker. When the double-talk period first begins during an echo at t_7 , the attenuation factor (k) is initially set to k_{down} and then gradually ramped-down until the double-talk period ceases at t_8 . At t_8 , a double-talk period has ended and an echo condition remains present. Normally, as explained above, when an echo condition remains present following a double-talk period gradual ramping-up of the attenuation factor (k) until it reaches k_{up} begins. However, since at t_8 the attenuation factor (k) is already less than k_{up} the input signal is simply muted-off at t_8 .

At the beginning and ends of words, voice segments are typically of low energy but still important for understanding. The smooth transition between states in the present invention allows otherwise unvoiced segments to get through, albeit in an attenuated fashion making the speech more understandable.

Referring now to Figure 6, there is shown an example of the operation of the present invention in a case where bursty noise is present at the far-end talker. As shown in Figure 6, each time a short segment of bursty noise appears at the far-end talker, a condition that is analagous to the echo conditions described above occurs. Thus, at the beginning of each bursty noise segment, the attenuation factor (k) begins ramping-up. However, since each bursty-noise

segment is relatively short, the bursty-noise segment ends before the system reaches k_{up} . At the end of each bursty noise segment, the attenuation factor begins ramping-down until it reaches 0 db. Unlike the ramping-down that typically occurs at the end of an echo condition, the ramping-down that occurs at the end of a bursty noise segment does not begin at k_{down} because, due to the brevity of each bursty noise segment, the attenuation factor (k) usually does not reach k_{down} during the ramping-up that occurs during the bursty noise segment. This gradual ramping-up and down of the attenuation factor during bursty noise segments stands in contrast to the operation achieved by prior art residual echo suppression element 18 which, in the identical situation, would entirely gate-off the input signal during each bursty noise segment. By gradually ramping-up and down the attenuation factor (k) for each bursty-noise segment (rather than entirely gating-off the input signal during each such segment), the present invention substantially reduces the "chopiness" in the audible signal that is typically heard by users of prior art echo cancellers.

Although the preferred embodiments of the present invention have been described above in connection with mobile telephones that use CDMA modulation, it will be understood by those skilled in the art that the present invention may be used for implementing an echo canceller in a mobile telephone system that uses alternative modulation techniques such as, for example, time-division multiple-access modulation systems. Moreover, it will be understood by those skilled in the art that the present invention may be used to improve echo cancellation in acoustic systems other than mobile telephone

systems, and that the teachings of the present invention may be used in non-acoustic echo cancellers such as those used in network applications.

The previous description of the preferred embodiments is provided to enable any person skilled in the art to make or use the present invention. The
5 various modifications to these embodiments will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other embodiments without the use of inventive faculty. Thus, the present invention is not intended to be limited to the methods and apparatuses shown herein but is to be accorded the widest scope consistent with the claims set forth
10 below.

What is claimed is:

CLAIMS

1. A method of canceling an echo signal, comprising the steps of:
 - 2 (A) providing an input waveform to an acoustic processor;
 - (B) determining whether said input waveform includes
 - 4 information representative of said echo signal; and
 - (C) forming an output waveform by attenuating a residual
 - 6 waveform with said acoustic processor if said input waveform includes
 - information representative of said echo signal;
 - 8 wherein said residual waveform is attenuated by an attenuation
 - factor that gradually changes from an initial attenuation value to a final
 - 10 attenuation value during said attenuation step.
2. The method of claim 1, wherein said attenuation factor decreases
- 2 linearly from said initial attenuation value to said final attenuation value during
- said attenuation step.
3. The method of claim 2, further comprising the step of:
 - 2 (D) after said residual waveform is attenuated by said final
 - attenuation amount during said attenuation step, muting said output
 - 4 waveform.

4. The method of claim 3, wherein said initial attenuation value is
2 equal to 0 db.

5. The method of claim 3, wherein said attenuation factor is
2 decreased from said initial attenuation value to said final attenuation value in
equal stepwise increments during said attenuation step.

6. The method of claim 5, wherein said attenuation factor is
2 decreased from said initial attenuation value to said final attenuation value at a
rate of 1 db every 5 ms during said attenuation step.

7. The method of claim 5, wherein step (C) further comprises the
2 steps of calculating an attenuation threshold and comparing said attenuation
threshold to said attenuation factor, and wherein said attenuation factor is
4 decreased by said stepwise increments until said attenuation factor is less than
said attenuation threshold.

8. The method of claim 7, wherein said input waveform is
2 representative of a signal that has been modulated in accordance with code-
division-multiple-access (CDMA) modulation.

9. The method of claim 8, wherein said attenuation threshold (K_{up}) is
2 calculated in accordance with the following equation:

$$K_{up} = \alpha ((M * 2^{32} * b_n S * G_{pred}) / (12 * E))^{0.5}$$

4 wherein E represents an energy estimate of said input waveform over M
samples, bnS is a background noise scale value for a uniformly distributed
6 random noise generator, and G_{pred} is the prediction gain of a LPC shaping filter
associated with said CDMA modulation.

10. The method of claim 1, wherein said echo signal is representative
2 of an acoustic echo resulting from coupling of a microphone and a speaker
located at a position associated with a far-end talker.

11. The method of claim 1, wherein said echo signal corresponds to
2 bursty noise supplied into a transmission channel at a position associated with a
far-end talker.

12. A method for adjusting an acoustic signal from a muted state to
2 an unmuted state by varying an attenuation factor applied to an acoustic signal
by an acoustic processor, comprising the steps of:

4 (A) providing said acoustic signal to an acoustic processor;

 (B) forming an output waveform from said acoustic processor
6 by adjusting said attenuation factor from the muted state to a first attenuation
value associated with said non-muted state;

8 (C) after said attenuation factor is adjusted to said first
attenuation value in step (B), forming said output waveform by gradually
10 changing said attenuation factor from said first attenuation value to a second
attenuation value;

12 wherein said input waveform is attenuated by a smaller amount
when said second attenuation value is applied to said acoustic signal than when
14 said first attenuation value is applied to said acoustic signal.

13. The method of claim 12, wherein said attenuation factor is
2 increased from said first attenuation value to said second attenuation value in
equal stepwise increments during step (C).

14. The method of claim 13, wherein said attenuation factor is
2 increased from said first attenuation value to said second attenuation value at a
rate of 1 db every 5 ms during said step (C).

15. The method of claim 13, wherein step (C) further comprises the
2 steps of comparing said attenuation factor to an attenuation threshold, and
wherein said attenuation factor is increased by said stepwise increments in step
4 (C) until said attenuation factor is greater than or equal to said attenuation
threshold.

16. The method of claim 15, wherein said attenuation threshold is
2 equal to 0 db.

17. The method of claim 12, wherein said input waveform is
2 representative of a signal that has been modulated in accordance with code-
division-multiple-access (CDMA) modulation.

18. The method of claim 17, wherein said second attenuation value
2 (K_{down}) is calculated in accordance with the following equation:

$$K_{\text{down}} = B((M * 2^{32} * \text{bnS} * G_{\text{pred}}) / (12 * E))^{0.5}$$

- 4 wherein E represents an energy estimate of said input waveform over M
samples, bnS is a background noise scale value for a uniformly distributed
6 random noise generator, and G_{pred} is the prediction gain of a LPC shaping filter
associated with said CDMA modulation.

19. The method of claim 12, wherein said echo signal is representative
2 of an acoustic blip occurring at a position associated with a near-end talker.

20. A system for canceling an echo signal, comprising:

- 2 (A) an acoustic processor that receives an input waveform;

- (B) an adaptive filter that determines whether said input
4 waveform includes information representative of said echo signal; and

- (C) said acoustic processor including a variable attenuator that
6 forms an output waveform by attenuating a residual waveform if said input
waveform includes information representative of said echo signal;


- 8 wherein said variable attenuator said residual waveform by an
attenuation factor that gradually changes from an initial attenuation value to a
10 final attenuation value if said input waveform includes information
representative of said echo signal.

21. A system for adjusting an acoustic signal from a muted state to an
2 unmuted state by varying an attenuation factor applied to an acoustic signal by
an acoustic processor, comprising:

4 (A) an acoustic processor that receives an acoustic signal;


(B) said acoustic processor including a variable attenuator that
6 forms an output waveform by first adjusting said attenuation factor from the
muted state to a first attenuation value associated with said non-muted state
8 and, after said attenuation factor is adjusted to said first attenuation value,
forming said output waveform by gradually changing said attenuation factor
10 from said first attenuation value to a second attenuation value;

wherein said input waveform is attenuated by a smaller amount
12 when said second attenuation value is applied to said acoustic signal than when
said first attenuation value is applied to said acoustic signal.



(PRIOR ART)

FIG. 1



(PRIOR ART)

FIG. 2




FIG. 3




FIG. 4






FIG. 5



MUTE

FIG. 6

INTERNATIONAL SEARCH REPORT

International Application No

PCT/US 01/02749

A. CLASSIFICATION OF SUBJECT MATTER

IPC 7 H04M9/08 H04B3/23

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H04M H04B

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, WPI Data, PAJ, INSPEC

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category °	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	WO 99 35814 A (ERICSSON GE MOBILE INC) 15 July 1999 (1999-07-15) page 3, line 27 -page 4, line 8 page 11, line 6 - line 13 page 11, line 31 -page 12, line 20 page 13, line 28 -page 14, line 23 claim 42	1-21
A	WO 98 30009 A (ERICSSON GE MOBILE INC) 9 July 1998 (1998-07-09) page 2, line 15 -page 3, line 11 page 6, line 14 - line 28 page 12, line 17 -page 13, line 26; figure 3	1-21

☐ Further documents are listed in the continuation of box C.

☒ Patent family members are listed in annex.

° Special categories of cited documents:

- *A* document defining the general state of the art which is not considered to be of particular relevance
- *E* earlier document but published on or after the international filing date
- *L* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)
- *O* document referring to an oral disclosure, use, exhibition or other means
- *P* document published prior to the international filing date but later than the priority date claimed

- *T* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
- *X* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
- *Y* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.
- *G* document member of the same patent family

Date of the actual completion of the international search

26 April 2001

Date of mailing of the international search report

28/05/2001

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2
NL - 2280 HV Rijswijk
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl.
Fax: (+31-70) 340-3016

Authorized officer

De Iulis, M

INTERNATIONAL SEARCH REPORT

information on patent family members

International Application No

PCT/US 01/02749

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
WO 9935814 A	15-07-1999	US 6160886 A	12-12-2000
		AU 1946899 A	26-07-1999
		BR 9813788 A	03-10-2000
		CN 1286863 T	07-03-2001
		EP 1046272 A	25-10-2000
WO 9830009 A	09-07-1998	AU 7893798 A	31-07-1998
		BR 9713809 A	25-01-2000
		CN 1247663 A	15-03-2000
		EP 0950309 A	20-10-1999
		US 6160886 A	12-12-2000
		US 6185300 B	06-02-2001